

Note: This datasheet may be out of date.

Please download the latest datasheet of CSTCR5M00G55-R0 from the official website of Murata Manufacturing

Co., Ltd.

https://www.murata.com/en-us/products/productdetail?partno=CSTCR5M00G55-R0

## CSTCR5M00G55-R0










## Appearance & Shape







### Features

MURATA's package technology expertise has enabled the development of the Chip "CERALOCK" with built-in load capacitors. High-density mounting can be realized because of the small package and the elimination of the need for an external load capacitor.

### Features

- 1. Oscillation circuits do not require external load capacitors.
- 2. The series is available in a wide frequency range.
- 3. The resonators are extremely small and have a low profile.
- 4. No adjustment is necessary for oscillation circuits.

# Applications

Other Usage

Consumer/Industrial



## Packaging Information

| Packaging | Specifications      | Minimum<br>Order Quantity |
|-----------|---------------------|---------------------------|
| R0        | 180mm Embossed Tape | 3000                      |

1 of 2

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with no ur sales representatives or product engineers before ordering.

2. This datasheet has early being passifications because there is no expense for datafacturing the product of the product of

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated : 2018/03/23



Note: This datasheet may be out of date

 $\underline{ Please \ download \ the \ latest \ data sheet \ of \ CSTCR5M00G55-R0 \ from \ the \ of \ icial \ website \ of \ Murata \ Manufacturing} }$ 

 $\underline{\text{Co., Ltd.}} \\ \text{https://www.murata.com/en-us/products/productdetail?partno=CSTCR5M00G55-R0} \\$ 

# CSTCR5M00G55-R0



| Shape                          | SMD           |
|--------------------------------|---------------|
| Frequency                      | 5.000MHz      |
| Frequency Tolerance            | ±0.5%         |
| Operating Temperature Range    | -20℃ to 80℃   |
| Frequency Shift by Temperature | ±0.2%         |
| Frequency Aging                | ±0.1%         |
| Wash                           | Not available |
| Resonant Impedance             | 60Ω           |
| Built-in Load Capacitance      | 39pF          |

2 of 2

### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering

